

FOR RENTAL MOD 600XB/1000 by Modulift

The Modulift Spreader is modular in length. Every spreader consists of 1 pair of End Units & Drop Links, with intermediate struts that can be bolted into the assembly to achieve different spans. The MOD 600XB/1000 has an assembled span ranging from 2 metres to 26m in 0.5m increments.







TABLE 1: COMPONENT LIST									
PART REF:	DESCRIPTION	WEIGHT / ITEM							
P1	END UNIT WLL 500t	870kg							
P2	DROP LINK WLL 500t	385kg							
P3	6.0m STRUT	2665kg							
P4	5.0m STRUT	2265kg							
P5	4.0m STRUT	1865kg							
P6	3.0m STRUT	1470kg							
P7	2.0m STRUT	1070kg							
P8	1.0m STRUT	675kg							
P9	0.5m STRUT	475kg							
P10	600t WIDE BODY SHACKLE	980kg							
P11	500t WIDE BODY SHACKLE	780kg							
P12	M24x90 Grade 10.9 HT BOLTS WASHERS	, NUTS &							





MOD 600XB/1000 - Beam Specification.

- Rated at 1000 tonnes SWL at 15 metres span (30° STV). See Load Table for SWL at longer spans.
- 'Sling to Vertical' angle, β , 45 degrees or less.
- End Units & Drop Links are rated at 500 tonnes WLL each (1000 tonnes combined capacity).
- Bolt tightening torque: 250Nm. Spanner size required: 36mm.
- Recommended additional equipment: Torque Wrench, Podger Spanner and Ring Spanner.


- Personnel using this system should be suitably trained, competent and have a clear understanding of Safe Slinging procedures.
- The use of Modulift equipment must be in accordance with the procedures laid down in the 'Lifting Operations and Lifting Equipment Regulations 1998' (LOLER).
- NEVER EXCEED STATED SWL ADHERE TO SWL IN TABLE 2, FOR PARTICULAR SLING ANGLE USED
- THE TOP SLING LENGTH IS CRITICAL TO THE SAFE USE OF THE SPREADER ADHERE TO TABLE 2.
- Ensure Drop Links hang down, and smaller shackles are connected to bottom hole of Drop Link.
- Do not under any circumstances hang load(s) from the tube or flanges the spreader is designed for axial compression - not bending.



FOR RENTAL MOD 600XB/1000 by Modulift

45° STV			Recommended								30° STV			
Span /m	SWL /t	Min Top sling Length/m	Configuration EU - End Unit (1m) STV = "SLINGTO VERTICAL' ANGLE, 8								Span /m	SWL /t	MinTop sling Length/m	
2	575		EU	EU						2	2	1000	2	
3	575	2.0	EU	1	EU						3	1000	3	
4	575	2.5	EU	2	EU						4	1000	4	
5	575	3.5	EU	3	EU						5	1000	5	
6	575	4.0	EU	3	1	EU					6	1000	6	
7	575	4.5	EU	3	2	EU					7	1000	7	
8	575	5.5	EU	6	EU						8	1000	8	
9	575	6.0	EU	6	1	EU					9	1000	9	
10	575	7.0	EU	6	2	EU					10	1000	10	
11	575	7.5	EU	6	3	EU					11	1000	11	
12	575	8.5	EU	3	6	1	EU				12	1000	12	
13	575	9.0	EU	3	6	2	EU				13	1000	13	
14	575	9.5	EU	6	6	EU					14	1000	14	
15	575	10.5	EU	6	6	1	EU				15	1000	15	
16	559	11.0	EU	6	6	2	EU				16	977	16	
17	514	12.0	EU	6	6	3	EU				17	899	17	
18	469	12.5	EU	1	6	6	3	EU			18	821	18	
19	427	13.0	EU	2	6	6	3	EU			19	749	19	
20	391	14.0	EU	6	6	6	EU				20	688	20	
21	354	14.5	EU	6	6	6	1	EU			21	623	21	
22	320	15.5	EU	6	6	6	2	EU			22	565	22	
23	289	16.0	EU	6	6	6	3	EU			23	512	23	
24	260	17.0	FU	1	6	6	6	3	FU		24	461	24	
25	234	17.5	EU	2	6	6	6	3	EU		25	416	25	
26	209	18.0	EU	1	2	6	6	6	3	EU	26	373	26	

To calculate the SWL at intermediate spans utilising the 0.5m strut, round up the span to the next longest span in Table 2, and use the stated SWL.



Assemble longer struts in the centre of

Sling angle is crucial to safe use of

the spreader configuration

assembly: 6

spreader

Recommended top sling types: Textile slings, cable laid wire rope slings or grommets. It is strongly recommended that a sling angle of 30° STV or less is used, to always ensure clearance between the sling and end unit. **Note:** Lengthening the slings can give greater clearance. Refer to Modulift supplier if in doubt.

ASSEMBLY PROCEDURE.

- 1. Check the ID plates on each Modulift component to ensure the correct size is used.
- 2. Lay out the Struts and End Units in the correct configuration (see table 2), laid on flats to prevent rolling.
- 3. Check that all pairs of flanges are clear from debris, sand etc. before connection.
- 4. Bolt the components together using bolts, nuts & washers provided. Tighten the bolts to a torque as shown overleaf, 20 bolts per connection*.
- 5. Place drop link inside the jaw of an end unit, with the larger hole of drop link lined up with the End Unit hole.
- 6. Place a top sling onto the body of a top shackle, and put jaw of top shackle over the end unit jaw.
- 7. Put top shackle pin through shackle, end unit jaw and drop link, and repeat for other spreader beam end.
- 8. Attach free ends of top slings to crane hook.
- g. Attach lower slings and shackles to lower holes of drop links, and attach them to the load to be lifted.

10. The assembled spreader beam and lifting rig must be thoroughly checked by a competent person prior to lifting.

- Do ensure to load the spreader through the drop links only. i.e. adhere to Fig. 1.
- Do keep the loaded spreader clear of obstacles any contact could cause beam failure.
- Do ensure correct use of appropriate top slings, do not twist any slings unnecessarily.
- · Do not hang any load from the spreader tube or flanges.
- Do not exceed stated SWL for that particular span adhere to table 2.
- · Do not rig the lower slings more than 6 degrees from vertical.
- When moving or positioning long struts or assemblies use tag lines to control movement.
- · Individual components can be heavy and extreme care must be taken if manual handling.
- *The number and grade of bolts is critical for the safe use of the spreader particularly at longer spans



Should you find your equipment is no longer of use, please dispose of in a responsible manner. Please contact Modulift if you need further guidance.



